

Preset Name: "UDA4_F1V1"

Signal Processor: Work WPE24 & WPE44

Description: Flat Preset.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processors Work WPE24 & WPE44. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

EQ	EQ Type / Freq	Gain (dB)	Q
1	Peak / 2150Hz	+4	2
2	Peak / 1420Hz	+1	3
3	Peak / 6070Hz	+2	2.4
4	Peak / 3410 Hz	-1	3.6

Filter	Frequency	Filter Order	Filter Type
High Pass	100Hz	4th (24dB/Oct)	Butterworth

Preset Name: "UDA4_Sh+3dBV1"

Signal Processor: Work WPE24 & WPE44

Description: +3dB on highs to improve intelligibility at long distances. Gain of the Shelving filter can be changed as needed.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processors Work WPE24 & WPE44. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

EQ	EQ Type / Freq	Gain (dB)	Q
1	Peak / 2150Hz	+4	2
2	Peak / 1420Hz	+1	3
3	Peak / 6070Hz	+2	2.4
4	Peak / 3410 Hz	-1	3.6
5	High Shelving / 4010	+3	0.5

Filter	Frequency	Filter Order	Filter Type
High Pass	100Hz	4th (24dB/Oct)	Butterworth