

Preset Name: "SN8\_F1V1"  
Signal Processor: Work WPE26N  
Description: Flat Preset.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processor Work WPE26N. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

- 1.- Peak 310Hz G=+2.3dB Q=+3
- 2.- Peak 440Hz G=+4.5dB Q=+2.3
- 3.- Peak 588Hz G=-2dB Q=+3
- 4.- Peak 4150Hz G=-3dB Q=+2.6

XOver

High Pass, 35Hz, 4th Order, Butterworth.

Preset Name: "SN8\_Sh+3dBV1"  
Signal Processor: Work WPE26N  
Description: +3dB on highs to improve intelligibility at long distances. Gain of the Shelving filter can be changed as needed.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processor Work WPE26N. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

- 1.- Peak 310Hz G=+2.3dB Q=+3
- 2.- Peak 440Hz G=+4.5dB Q=+2.3
- 3.- Peak 588Hz G=-2dB Q=+3
- 4.- Peak 4150Hz G=-3dB Q=+2.6
- 5.- HighShelving 4000Hz G=+3dB Q=0.5

XOver

High Pass, 35Hz, 4th Order, Butterworth.