

MAX 3 BT

This new mixer belonging to the MAX series is ideal for small installations, thanks to its small size and versatility, since it integrates a USB interface which allows to be connected to an external device and work as a sound card. This new model incorporates a Bluetooth module, that makes possible to connect the MAX 3 BT with mobile devices such as smartphones or tablets and play MP3 files through the mixer. Its size and weight (480 gr) makes it ideal for conferences, mobile shows...



Features:

- 1 mic/line input channel with Combo connection and balanced line input
- 1 stereo input channel with RCA jack
- Ultra-low noise discrete MIC preamp with +20V Phantom Power
- 2 band EQ (High and Low) in mono and stereo channels
- 1 Gain control in channel mono & master
- Peak LED in channel mono & master
- 2 RCA- Track inputs & 2 RCA Track outputs
- 2 RCA- Track inputs assign to Main Mix Monitors outputs
- Main Mix & Monitor outputs use 3.5mm stereo jack
- Built-in stereo USB/Audio interface
- Either USB bus powered or external adapter
- Bluetooth player function