

Preset Name: "SN6_F1V1"
Signal Processor: Work WPE26N
Description: Flat Preset.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processor Work WPE26N. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

- 1.- Peak 350Hz G=+4dB Q=4
- 2.- Peak 500Hz G=+4dB Q=6
- 3.- Peak 5700Hz G=-5dB Q=1
- 4.- Peak 10700Hz G=8dB Q=1.8

XOver

High Pass, 45Hz, 4th Order, Butterworth.

Preset Name: "SN6_Sh+3dBV1"
Signal Processor: Work WPE26N
Description: +3dB on highs to improve intelligibility at long distances. Gain of the Shelving filter can be changed as needed.

Warning!: Limiter settings have to be adjusted by the user.

Warning!: These presets are intended for the signal processor Work WPE26N. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

- 1.- Peak 350Hz G=+4dB Q=4
- 2.- Peak 500Hz G=+4dB Q=6
- 3.- Peak 5700Hz G=-5dB Q=1
- 4.- Peak 10700Hz G=8dB Q=1.8
- 5.- HighShelving 4000Hz G=+3dB Q=0.5

XOver

High Pass, 45Hz, 4th Order, Butterworth.