Preset Name: "SL218RDforSL101"
Signal Processor: Work WPE26N
Description: Preset for Subwoofer SL218RD and SL101. Delay is setup so the SL101 will be in phase when the subwoofers are right below the cluster.

Warning!: Limiter settings have to be adjusted by the user. Balance between the SL101 units and the subwoofers has to be adjusted by the user.

Warning!: These presets are intended for the signal processor Work WPE26N. Due to the fact that Qs are not calculated the same way in different signal processors, if a different signal processor is used non optimum electric curves might result, compromising the performance of the system.

MASTER
Gain = +0dB

INPUT
Gain = +10dB

SUBWOOFER
Gain = -7dB
EQ1.- Peak 67Hz G=+2dB Q=3

Delay: 9.9ms

XOver
High Pass: 20Hz, 4th Order, Butterworth.
Low Pass: 65Hz, 4th Order, Butterworth